

## **200A, 25 kV Class Loadbreak Portable Feed Thru**



APPLICATION

The Chardon 200A, 25kV Class Loadbreak Portable Feed Thru is designed to be installed on a parking stand, attached to a transformer or other apparatus. Two bushing insert loadbreak interfaces can be mated with an elbow arrester, a loadbreak elbow, or an insulated cap. When mated with other products that meets IEEE Standard 386, the portable feed thru provides a fully shielded, submersible connection for loadbreak operation.

PRODUCTION TESTS

Tests conducted in accordance with IEEE/ANSI Standard 386.

- / Partial Discharge – 19 kV ≤5pC
- / AC 1 Minute Withstand – 40 kV

Tests conducted in accordance with Chardon manufacturing process requirements:

- / Physical Inspection
- / Periodic Dissection
- / Periodic X-ray Analysis

VOLTAGE RATINGS

Voltage Class	25 kV
Max. Rating Phase to Phase	26.3 kV
Max. Rating Phase to Ground	15.2 kV
AC 1 Minute Withstand	40 kV
DC 15 Minute Withstand	78 kV
BIL and Full Wave Crest	125 kV
Partial Discharge	19 kV≤5pC


•25LPFT200-051116-REV01

The Chardon Portable Feed Thru meets all the requirements of IEEE Standard 386, and is fully interchangeable with competitor's products and mating products that also meet IEEE Standard 386. The indicating ring design eliminates the guesswork of loadbreak installation, it provides feedback to determine if the elbow is properly installed.

CURRENT RATINGS

Description	Test Parameters
Continuous	200 amps rms
Switching	10 operations at 200 amps rms at 26.3 kV
Fault Close	10,000 amps rms symmetrical at 26.3 kV for 0.17 s after 10 consecutive successful switching operations
Short Time	• 10,000 amps rms symmetrical for 0.17 s • 3,500 amps rms symmetrical for 3.0 s

DETAILED COMPOSITION OF THE CHARDON LOADBREAK PORTABLE FEED THRU




ORDERING INFORMATION

Each Portable Feed Thru kit includes the following:

- / Portable Feed Thru with Bracket
- / Shipping Cap (not for energized operation)
- / Stainless Steel Bail Assembly
- / Installation Instruction Sheet

To order the 25kV Class Portable Feed Thru Kit, use the P/N below:

25kV Loadbreak Portable Feed Thru	25-LPFT200
-----------------------------------	------------







**ANHUI CHARDON ELECTRIC LTD.**

No.808 Taiji Road Economic Develop Zone of Guangde  
County Anhui China

Tel: 0563-2216688

Fax: 0563-2251806

**CHARDON TAIWAN CORPORATION**

No.37 Min-Chie Road, Tung Lo Industrial Park, Miao Li,  
Taiwan 366

Tel: +886-37-984385

Fax: +886-37-984770

**SHANGHAI CHARDON ELECTRIC LTD.**

Room 1202, office building No.399, Yun Gu Road ,  
Jiading district, Shanghai, China 201801

Tel: +86-21-39105900

Fax: +86-21-391059166

[www.chardongroup.com](http://www.chardongroup.com) [info@chardongroup.com](mailto:info@chardongroup.com)